

ESP32

De ESP32 is een budgetserie van laag-vermogen microcontrollers met geïntegreerde Wi-Fi en dual-mode Bluetooth. De ESP32-serie maakt gebruik van een Tensilica Xtensa LX6- microprocessor in zowel dual-core als single-core uitvoering. De ESP32 is gemaakt en ontwikkeld door Espressif Systems, een in Shanghai gevestigd Chinees bedrijf, en wordt vervaardigd door TSMC met behulp van hun 40nm-proces. Het is een opvolger van de ESP8266 microcontroller. Deze microcontroller is erg populair bij hobbyisten voor het ontwikkelen van Internet of things applicaties.

De ESP32 is verkrijgbaar in diverse uitvoeringen. Zelf heb ik een ESP32 Wroom 32D (38 pins) aangeschaft om mee te experimenteren.

[ESP32-ESP-WROOM-32.jpg](#)

Pin bezetting ESP32 Wroom 32 (38 pins)

[ESP32-Pinout.png](#)

[ESP32-Pinout-2.jpg](#)

ESP32-WROOM-32 (ESP-WROOM-32) Pin Configuration

Pin Category	Pin Name	Details
Power	Micro-USB, 3.3V, 5V, GND	Micro-USB: ESP32 can be powered through USB port 5V: Regulated 5V can be supplied to this pin which is we be again regulated to 3.3V by on board regulator, to power the board. 3.3V: Regulated 3.3V can be supplied to this pin to power the board. GND: Ground pins.
Enable	En	The pin and the button resets the microcontroller.
Analog Pins	ADC1_0 to ADC1_5 and ADC2_0 to ADC2_9	Used to measure analog voltage in the range of 0-3.3V.12-bit 18 Channel ADC

DAC pins	DAC1 and DAC2	Used for Digital to analog Conversion
Input/output Pins	GPIO0 to GPIO39	Totally 39 GPIO pins, can be used as input or output pins. 0V (low) and 3.3V (high). But pins 34 to 39 can be used as input only
Capacitive Touch pins	T0 to T9	These 10 pins can be used as touch pins normally used for capacitive pads
RTC GPIO pins	RTCIO0 to RTCIO17	These 18 GPIO pins can be used to wake up the ESP32 from deep sleep mode.
Serial	Rx, Tx	Used to receive and transmit TTL serial data.
External Interrupts	All GPIO	Any GPIO can be used to trigger an interrupt.

PWM	All GPIO	16 independent channels are available for PWM any GPIO can be made to work as PWM through software
VSPi	GPIO23 (MOSI), GPIO19(MISO), GPIO18(CLK) and GPIO5 (CS)	Used for SPI-1 communication.
HSPI	GPIO13 (MOSI), GPIO12(MISO), GPIO14(CLK) and GPIO15 (CS)	Used for SPI-2 communication.
IIC	GPIO21(SDA), GPIO22(SCL)	Used for I2C communication.
AREF	AREF	To provide reference voltage for input voltage.

ESP32-WROOM-32 (ESP-WROOM-32) Technical features

Microprocessor	Tensilica Xtensa LX6
Maximum Operating Frequency	240MHz
Operating Voltage	3.3V
Analog Input Pins	12-bit, 18 Channel
DAC Pins	8-bit, 2 Channel
Digital I/O Pins	39 (of which 34 is normal GPIO pin)
DC Current on I/O Pins	40 mA
DC Current on 3.3V Pin	50 mA

SRAM	520 KB
Communication	SPI(4), I2C(2), I2S(2), CAN, UART(3)
Wi-Fi	802.11 b/g/n
Bluetooth	V4.2 – Supports BLE and Classic Bluetooth

Shop

[AliExpress](#)

Revision #5

Created 10 September 2023 15:46:42 by Alex

Updated 10 September 2023 15:53:21 by Alex